



IC-441WH Inside Remote Control

Inside remote control can be installed in a convenient location to control IS-76, ISA-78 and IS-82 speakers. Recessed installation.

- Use with one 25 Ohm speaker (IS-76, ISA-78, IS-82)

Model No.	Overall Size
IC-441WH	7" x 4" x 1 1/16"
Panel Projects	7/8"

FEATURES:

- Bright White
- One button talk/listen operation with Inside/Patio, Door Talk, "Private" and End Call buttons, volume control
- Control radio or CD from remote speakers; ON/Off, select memory radio stations, select CD track
- Recessed Mounts
- IR-91 rough-in

SPECIFICATIONS:

Wire IW-6/IW-2 or IW-6UL/IW-2UL
 Max. wire length of (1) remote control 750 ft.
 Max. wire length of all remote speakers/controls 4000 ft.
 Maximum No. of Speakers per Control one
 Type of Speaker 25 ohm
 Rough-in Model No. IR-91
 Warranty 2 Year